

# Adapter, N Female to BNC Male

# NF-BM50+

## Typical Performance Data

FREQUENCY (MHz)	INSERTION LOSS (dB)	N-FEMALE VSWR (:1)	BNC-MALE VSWR (:1)
0.3	0.08	1.00	1.00
1.0	0.04	1.00	1.00
5.0	0.03	1.00	1.00
10	0.03	1.00	1.00
50	0.03	1.01	1.01
100	0.03	1.01	1.01
200	0.04	1.02	1.01
300	0.04	1.03	1.01
400	0.04	1.04	1.02
500	0.04	1.05	1.02
600	0.05	1.06	1.02
700	0.05	1.06	1.02
800	0.06	1.07	1.03
900	0.06	1.07	1.03
1000	0.06	1.08	1.03
1200	0.06	1.08	1.03
1400	0.06	1.08	1.03
1600	0.07	1.08	1.03
1800	0.07	1.07	1.02
2000	0.07	1.06	1.01