

Band Pass Filter

BPF-EDU1475+

Typical Performance Data

FREQUENCY (MHz)	INSERTION LOSS (dB)	RETURN LOSS (dB)	FREQUENCY (MHz)	GROUP DELAY (nsec)
1.0	79.01	0.22	264	56.99
50	87.92	0.39	265	53.36
100	91.51	0.52	266	50.31
242	48.36	0.80	267	47.67
252	29.17	1.51	268	45.49
257	15.94	3.25	269	43.73
260	8.53	7.67	270	42.42
264	4.33	22.30	271	41.48
267	3.54	19.43	272	40.87
275	3.12	14.43	273	40.44
283	3.52	16.36	273	40.36
287	4.54	18.72	274	40.21
290	8.04	9.43	275	40.11
295	19.26	2.58	276	40.20
300	28.71	1.59	277	40.45
314	47.00	1.01	278	40.86
500	100.38	0.84	279	41.39
1000	94.28	1.23	280	41.98
1500	75.65	1.46	281	42.56
2000	63.83	1.77	282	43.15
2500	48.56	1.77	283	43.97
3000	39.56	2.27	284	45.39
3500	35.68	2.11	285	47.80
4000	22.28	3.73	286	51.50

REV. X1
BP-EDU1475+
101031
Page 1 of 1



IF/RF MICROWAVE COMPONENTS • ISO 9001 ISO 14001 AS 9100 CERTIFIED RoHS compliant
P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 Fax (718) 332-4661



The Design Engineers Search Engine finds the model you need, Instantly • For detailed performance specs & shopping online see

