Frequency Mixer

ASK-2

Level 7 (LO Power +7 dBm)

Important Note

This is a non-catalog model and can be manufactured on specific request. Pricing and delivery information can be supplied upon request.



Please click "Back", and then click "Contact Us" for Applications support.

CASE STYLE: W38

ELECTRICAL SPECIFICATIONS 50Ω @ +25°C						
Parameter		Min.	Тур.	Max.	Units	
Frequency	LO (fL to fU)	1		1000	MHz	
	RF (fL to fU)	1		1000	MHz	
	IF	0		1000	MHz	
Conversion Loss	mid band		6.8	8.0	dB	
	Total Range			9.8	dB	
LO-RF Isolation	Low Range	40	60		dB	
	Mid Range	18	35		dB	
	Upper Range	16	26		dB	
LO-IF Isolation	Low Range	30	50		dB	
	Mid Range	17	25		dB	
	Upper Range	10	15		dB	
1 dB Comp. Input Power			+1		dBm	

Notes: Low Range = [fL to 10fL] mid band = [2fL to fU/2] Mid Range = [10fL to fU/2]

Upper Range = [fU/2 to fU]

Non-hermetic

ASK plug-in mounting case X65

MAXIMUM RATINGS				
Operating Temperature	-40°C to 85°C			
Storage Temperature	-55°C to 100°C			
RF Power	50mW			
IF Current	40mA			

PIN CONNECTIONS			
LO	1		
RF	4		
IF	5		
GROUND	2, 3, 6		

Electrical Schematics

