Non-Catalog Model

RF Transformer Impedance Ratio : 1.22

Important Note

This is a non-catalog model and can be manufactured on specific request. Pricing and delivery information can be supplied upon request.

Please click "Back", and then click "Contact Us" for Applications support.



CASE STYLE : H16


ELECTRICAL SPECIFICATIONS 50Ω @ +25°C					
Parameter		Min.	Тур.	Max.	Units
Frequency		0.005		100	MHz
Insertion Loss *	3 dB Bandwidth		0.005 - 100		MHz
	2 dB Bandwidth		0.01 - 50		MHz
	1 dB Bandwidth		0.05 - 25		MHz

Notes:

* Insertion Loss is referenced to mid-band loss, 0.08dB typ. Impedance Ratio = Secondary / Primary

MAXIMUM RATINGS			
Operating Temperature	-55°C to 100°C		
Storage Temperature	-55°C to 100°C		
RF Power	0.25 W		
DC Current	30 mA		

Configuration : D





INTERNET http://www.minicircuits.com P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 Fax (718) 332-4661 Distribution Centers NORTH AMERICA 800-654-7949 • 417-335-5935 • Fax 417-335-5945 • EUROPE 44-1252-832600 • Fax 44-1252-837010 Mini-Circuits ISO 9001 & ISO 14001 Certified

REV. X1 FT1.22-1 060808 Page 1 of 1

FT1.22-1