## **NON-CATALOG**

# **Frequency Synthesizer**

KSN-1970A-219+

 $50\Omega$ 

1849.6 to 1969.92 MHz

## **The Big Deal**

- Low phase noise and spurious
- Robust design and construction
- Small size 0.80" x 0.58" x 0.15"



CASE STYLE: DK1042

#### **Product Overview**

The KSN-1970A-219+ is a Frequency Synthesizer, designed to operate from 1849.6 to 1969.92 MHz for TD-SCDMA applications. The KSN-1970A-219+ is packaged in a metal case (size of  $0.80" \times 0.58" \times 0.15"$ ) to shield against unwanted signals and noise.

## **Key Features**

Feature	Advantages
Low phase noise and spurious: • Phase Noise: -93 dBc/Hz typ. @ 10 kHz offset • Comparison Spurious: -107 dBc typ. • Reference Spurious: -103 dBc typ.	Low phase noise and spurious improve system EVM (Error Vector Magnitude).
Robust design and construction	To enhance the robustness of KSN-1970A-219+, each internal component is secured to the substrate with chip bonder, thereby eliminating the risk of tombstoning during subsequent solder reflow operations by the customer.
Small size, 0.80" x 0.58" x 0.15"	The small size enables the KSN-1970A-219+ to be used in compact designs.

For detailed performance specs & shopping online see web site

# Frequency Synthesizer

KSN-1970A-219+

1849.6 to 1969.92 MHz  $50\Omega$ 

#### **Features**

- Integrated VCO + PLL
- Low phase noise and spurious
- · Robust design and construction
- Low operating voltage (VCC VCO=+5V, VCC PLL=+5V)
- Small size 0.80" x 0.58" x 0.15"



CASE STYLE: DK1042

+ RoHS compliant in accordance with EU Directive (2002/95/EC)

The +Suffix has been added in order to identify RoHS Compliance. See our web site for RoHS Compliance methodologies and qualifications.


#### **Applications**

TD-SCDMA

#### **General Description**

The KSN-1970A-219+ is a Frequency Synthesizer, designed to operate from 1849.6 to 1969.92 MHz for TD-SCDMA applications. The KSN-1970A-219+ is packaged in a metal case (size of 0.80" x 0.58" x 0.15") to shield against unwanted signals and noise. To enhance the robustness of KSN-1970A-219+, each internal component is secured to the substrate with chip bonder, thereby eliminating the risk of tombstoning during subsequent solder reflow operations by the customer.

#### Simplified Schematic



& shopping online see web site

P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 Fax (718) 332-4661 The Design Engineers Search Engine Provides ACTUAL Data Instantly at minicipouits.com IF/RF MICROWAVE COMPONENTS

#### Electrical Specifications (over operating temperature -40°C to +85°C)

Parame	eters							Te	st Condit	ions	Mi	n.	Тур.		Max.	U	nits
Frequency	y Range								-		184	9.6	-	1	969.92	N	ЛHz
Step Size	p Size					-			-		1280		-	ŀ	кНz		
Settling Ti	ime							Within ± 1 kHz			-		5		-	m	Sec
Output Po	wer								-		+2	2	+5		+7	d	IBm
								@ 100	) Hz offset		-		-79		-		
					[	@ 1 kl	Hz offset		-		-88		-79		1 1		
SSB Phas	se Noise						[	@ 101	kHz offset		-		-93		-89	dE	3c/Hz
								@ 100	kHz offset		-		-124		-120		
								@ 1 M	1Hz offset		-		-146		-142		
Integrated	I SSB Phase Nois	е						@1 k⊦	Hz to 5 MHz		-		-47		-41	C	dBc
Reference	Spurious Suppre	ession						Ref. F	req. 76.8 MH	ŀz	-		-103		-85		
Comparis	on Spurious Supp	ression						Step S	Size 1280 kH	z	-		-107		-85		dBc
Non - Har	monic Spurious S	uppress	ion						-		-		-90		-		JDC
Harmonic	Suppression								-		-		-46		-25	-25	
VCO Sup	ply Voltage							5.00			4.75 5.00			5.25		V	
PLL Supp	PLL Supply Voltage					5.00			4.7	'5	5.00		5.25	; <b>v</b>			
VCO Sup	ply Current							-			-		27		33 mA		mΛ
PLL Supp	ly Current							-			-		14		22	'	ША
		F	requ	ency				76.8 (sine wave)			-		76.8		-	N	ЛHz
Reference	e Input	A	Amplitude				1		-		1		-	١	V <sub>P-P</sub>		
(External)		1	nput i	mpedar	nce			-			-		100		-	I	ΚΩ
		F	Phase	Noise	@ 1 kHz 0	ffset		-			-		-130		-	dE	Bc/Hz
RF Outpu	t port Impedance							-			-		50		-		Ω
Input Logi	c Level	1	nput l	nigh vol	tage				-		4.2	20	-		-		V
IIIput Logi	C Level	1	nput l	ow volta	age				-		-		-		0.95		V
Digital Loc	ck Detect	L	ocke	d					-		4.3	35	-		5.25		V
Digital Lot	CK Delect	ι	Jnlocl	ked					-		-		-		0.40		V
Frequency	y Synthesizer PLL	-							-		ADF4	113					
PLL Progr	ramming								-				V CMOS	3			
	F_Register NOTE 2	Prescale	Value	Power- Down 2	Current S	Setting 2	Cu Set	ırrent tting 1	Timer Counter Control	Fastlock Mode	Fastlock Enable	CP Three- State	PD Polarity	Muxout Control	Power- Down 1	Counter Reset	Control Bits
	i _i legistei	10		0	11	1	1	11	0000	0	0	0	1	001	0	0	10
Register	N_Register	Reser	served CP Gain			13-E	Bit B Counter				6-Bit A Counter				Control Bits		
Мар <sup>NOTE 1</sup>	@1969.92MHz	00		1				000000110000					000011				01
	P. Pogistor	Reserved	DLY	SYNC	Lock Detect Precision	Test Mode Bits		Backlash /idth			14-BIT	Reference	e Counter, R				Control Bits
R_Register		0	0	0	1	00	_	00			000	000001	11100				00

Note 1: Registers Load Sequence: Initialization Register, F Register, R Register, N Register.

Note 2: For the Initialization Register use Register F with Control Bits 11.

#### **Absolute Maximum Ratings**

Parameters	Ratings
VCO Supply Voltage	6V
PLL Supply Voltage	6V
VCO Supply Voltage to PLL Supply Voltage	N.A
Reference Frequency Voltage	-0.3Vmin,VCC PLL +0.3Vmax
Data, Clock, LE Levels	-0.3Vmin,VCC PLL +0.3Vmax
Operating Temperature	-40°C to +85°C
Storage Temperature	-55°C to +100°C

Permanent damage may occur if any of these limits are exceeded



P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 Fax (718) 332-4661 The Design Engineers Search Engine Provides ACTUAL Data Instantly at minicircuits.com IF/RF MICROWAVE COMPONENTS

#### **Typical Performance Data**

FREQUENCY	PO	POWER OUTPUT			VCO CURRENT			PLL CURRENT			
(MHz)		(dBm)			(mA)			(mA)			
` ′	-45°C	+25°C	+85°C	-45°C	+25°C	+85°C	-45°C	+25°C	+85°C		
1849.60	5.01	5.02	5.05	26.17	27.19	27.99	11.30	13.42	15.31		
1861.12	5.03	5.03	5.04	26.14	27.16	27.97	11.41	13.55	15.44		
1876.48	5.10	5.08	5.07	26.09	27.12	27.94	11.56	13.71	15.62		
1891.84	5.15	5.14	5.11	26.06	27.09	27.92	11.33	13.48	15.39		
1907.20	5.16	5.14	5.12	26.06	27.08	27.91	11.49	13.64	15.56		
1922.56	5.16	5.11	5.08	26.01	27.03	27.88	11.63	13.80	15.72		
1937.92	5.20	5.11	5.05	25.93	27.00	27.82	11.40	13.56	15.48		
1953.28	5.24	5.13	5.04	25.87	26.92	27.79	11.55	13.72	15.65		
1968.64	5.27	5.14	5.03	25.84	26.89	27.76	11.32	13.48	15.41		
1969.92	5.28	5.13	5.03	25.83	26.92	27.76	11.33	13.49	15.43		

FREQUENCY	HARMONICS (dBc)								
(MHz)		F2			F3				
, ,	-45°C	+25°C	+85°C	-45°C	+25°C	+85°C			
1849.60	-60.99	-62.76	-64.23	-51.20	-52.12	-54.29			
1861.12	-63.11	-65.65	-65.25	-50.83	-52.35	-53.21			
1876.48	-60.89	-65.54	-66.58	-48.95	-50.56	-51.74			
1891.84	-57.39	-64.23	-66.27	-47.17	-48.19	-50.16			
1907.20	-59.64	-67.87	-64.26	-45.06	-49.60	-47.65			
1922.56	-57.23	-70.87	-62.65	-44.95	-46.69	-48.60			
1937.92	-53.38	-64.28	-62.85	-43.79	-45.75	-46.90			
1953.28	-53.03	-67.23	-60.74	-43.94	-46.94	-47.06			
1968.64	-55.60	-68.09	-57.89	-43.53	-45.26	-46.03			
1969.92	-55.36	-68.20	-58.37	-43.52	-45.43	-45.97			

FREQUENCY	PH	IASE NOIS	E (dBc/Hz	) @OFFSE	TS						
(MHz)		+25°C									
. ,	100Hz	1kHz	10kHz	100kHz	1MHz						
1849.60	-78.82	-88.00	-95.08	-125.33	-146.30						
1861.12	-78.49	-89.63	-94.44	-125.12	-146.56						
1876.48	-80.19	-90.49	-93.30	-125.05	-146.55						
1891.84	-78.48	-88.22	-92.58	-124.77	-146.40						
1907.20	-79.22	-88.17	-92.73	-124.78	-146.36						
1922.56	-78.20	-90.51	-92.80	-124.48	-146.28						
1937.92	-81.47	-87.30	-92.60	-124.09	-145.47						
1953.28	-80.76	-88.25	-92.83	-123.61	-145.06						
1968.64	-78.62	-88.46	-93.50	-123.64	-145.41						
1969.92	-77.59	-87.12	-93.15	-123.49	-145.13						

FREQUENCY	PHASE NOISE (dBc/Hz) @OFFSETS							
(MHz)			-45°C					
. ,	100Hz	1kHz	10kHz	100kHz	1MHz			
1849.60	-81.69	-89.49	-95.12	-125.75	-147.35			
1861.12	-79.98	-88.90	-94.40	-125.57	-147.01			
1876.48	-79.78	-88.53	-93.96	-125.28	-146.93			
1891.84	-79.07	-89.06	-92.70	-125.08	-147.00			
1907.20	-80.01	-89.60	-92.62	-124.91	-146.78			
1922.56	-78.57	-88.42	-92.67	-124.53	-146.63			
1937.92	-78.79	-89.73	-92.37	-123.91	-146.32			
1953.28	-80.80	-86.53	-93.04	-123.63	-145.56			
1968.64	-79.46	-88.19	-93.04	-123.33	-145.24			
1969.92	-79.33	-86.47	-93.01	-123.23	-145.38			

EDECHENCY	PH	PHASE NOISE (dBc/Hz) @OFFSETS					
FREQUENCY (MHz)			+85°C				
	100Hz	1kHz	10kHz	100kHz	1MHz		
1849.60	-77.78	-87.66	-94.18	-124.52	-145.59		
1861.12	-81.01	-87.93	-93.16	-124.42	-145.89		
1876.48	-77.85	-87.87	-92.28	-124.13	-145.59		
1891.84	-78.90	-86.10	-91.68	-124.13	-145.64		
1907.20	-78.10	-86.38	-92.11	-124.03	-145.70		
1922.56	-78.40	-85.74	-91.96	-123.99	-145.63		
1937.92	-79.64	-83.98	-91.88	-123.46	-145.29		
1953.28	-77.24	-86.12	-92.08	-123.38	-145.08		
1968.64	-76.93	-83.29	-92.45	-123.45	-144.86		
1969.92	-78.34	-85.61	-92.15	-123.24	-144.91		

## **NON-CATALOG**

COMPARISON SPURIOUS ORDER	COMPARISON SPURIOUS  @Fcarrier  1849.6MHz+(n*Fcomparison)  (dBc) note 1			COMPARISON SPURIOUS @Fcarrier 1909.76MHz+(n*Fcomparison) (dBc) note 1			COMPARISON SPURIOUS  @Fcarrier  1969.92MHz+(n*Fcomparison)  (dBc) note 1		
n	-45°C	+25°C	+85°C	-45°C	+25°C	+85°C	-45°C	+25°C	+85°C
-5	-102.05	-103.91	-108.38	-111.20	-118.98	-116.43	-119.98	-126.27	-114.85
-4	-116.05	-122.66	-127.03	-112.84	-113.52	-112.94	-121.19	-128.52	-113.45
-3	-122.26	-116.60	-117.00	-109.08	-115.34	-113.63	-114.78	-123.21	-110.18
-2	-121.42	-110.99	-111.34	-107.25	-104.31	-107.29	-115.78	-121.54	-108.55
-1	-118.04	-107.43	-104.62	-95.29	-102.07	-98.39	-110.16	-112.62	-101.17
o <sup>note 2</sup>	-	-	-	-	-	-	-	-	-
+1	-119.96	-108.73	-104.61	-95.30	-102.50	-96.85	-111.03	-108.31	-99.86
+2	-119.87	-111.79	-109.36	-105.59	-102.27	-105.56	-116.89	-115.29	-107.82
+3	-119.15	-117.64	-117.39	-107.15	-113.80	-111.96	-122.11	-112.30	-108.02
+4	-117.98	-116.33	-118.79	-111.91	-110.03	-111.09	-125.63	-118.15	-113.39
+5	-104.74	-111.15	-117.40	-111.89	-113.36	-114.20	-127.19	-119.85	-113.07

Note 1: Comparison frequency 1280 kHz

Note 2: All spurs are referenced to carrier signal (n=0).

REFERENCE SPURIOUS ORDER	REFERENCE SPURIOUS  @Fcarrier  1849.6MHz+(n*Freference)  (dBc) note 3			REFERENCE SPURIOUS  @Fcarrier  1909.76MHz+(n*Freference)  (dBc) note 3			REFERENCE SPURIOUS  @Fcarrier  1969.92MHz+(n*Freference)  (dBc) note 3		
n	-45°C	+25°C	+85°C	-45°C	+25°C	+85°C	-45°C	+25°C	+85°C
-5	-116.94	-117.84	-120.73	-111.51	-115.61	-119.78	-112.02	-119.31	-119.36
-4	-104.35	-104.93	-107.75	-100.62	-105.37	-107.79	-98.26	-103.70	-104.20
-3	-94.75	-97.51	-100.97	-102.50	-109.57	-107.84	-109.33	-112.78	-110.14
-2	-97.27	-98.70	-99.06	-96.52	-98.08	-99.52	-97.13	-97.33	-98.07
-1	-95.95	-101.47	-103.90	-96.20	-101.94	-105.80	-95.98	-100.40	-105.25
o <sup>note 4</sup>	-	-	-	-	-	-	-	-	-
+1	-98.30	-103.83	-107.13	-99.74	-103.21	-108.10	-99.69	-105.62	-108.73
+2	-96.93	-96.68	-98.25	-98.55	-98.40	-99.61	-98.20	-98.67	-100.04
+3	-95.41	-97.93	-99.60	-102.26	-103.37	-107.86	-104.54	-105.02	-109.49
+4	-97.65	-99.92	-102.04	-98.27	-102.23	-103.97	-97.68	-100.64	-98.24
+5	-111.14	-112.69	-118.03	-110.29	-112.66	-115.49	-113.09	-111.77	-116.86


Note 3: Reference frequency 76.8 MHz

Note 4: All spurs are referenced to carrier signal (n=0).




## **NON-CATALOG**

#### **Typical Performance Curves**





#### 2nd HARMONIC Vs FREQUENCY -40 2nd HARM. SUPPRESSION (dBc) -45°C +25°C -50 +85°C -70 -80 1849.60 1879.68 1909.76 1939.84 1969.92 FREQUENCY (MHz)





& shopping online see web site


ISO 9001 ISO 14001 AS 9100 CERTIFIED
P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 Fax (718) 332-4661 The Design Engineers Search Engine Provides ACTUAL Data Instantly at minimal pro IF/RF MICROWAVE COMPONENTS















& shopping online see web site


ISO 9001 ISO 14001 AS 9100 CERTIFIED
P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 Fax (718) 332-4661 The Design Engineers Search Engine Provides ACTUAL Data Instantly at minimal pro IF/RF MICROWAVE COMPONENTS















& shopping online see web site

P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 Fax (718) 332-4661 The Design Engineers Search Engine Provides ACTUAL Data Instantly at minicipality. IF/RF MICROWAVE COMPONENTS

#### **Pin Configuration**




#### **Pin Connection**

Pin Number	Function
1	VCC PLL
2	GND
3	REF IN
4	GND
5	VCC VCO
6	GND
7	RF OUT
8	GND
9	LOCK DET
10	CLOCK
11	DATA
12	LE
13	GND
14	GND

#### **Recommended Application Circuit**


Note: REF IN and RF OUT ports are internally AC coupled.



& shopping online see web site

ISO 9001 ISO 14001 AS 9100 CERTIFIED
P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 Fax (718) 332-4661 The Design Engineers Search Engine Provides ACTUAL Data Instantly at minicipal Provides ACTUAL Data Instantly ACTUAL Data In IF/RF MICROWAVE COMPONENTS

#### **Device Marking**



#### **Additional Detailed Technical Information**

Additional information is available on our web site. To access this information enter the model number on our web site home page.

Case Style: DK1042

Tape & Reel: TR-F28

Suggested Layout for PCB Design: PL-249

**Evaluation Board:** TB-567+

**Environment Ratings:** ENV03T2

Mini-Circuits

ISO 9001 ISO 14001 AS 9100 CERTIFIED

For detailed performance spect & shopping online see web site