NON-CATALOG

Low Pass Filter

LFCN-2750

 50Ω

DC⁽¹⁾ to 2750 MHz

Generic photo used for illustration purposes only

CASE STYLE: FV1206

Maximum Ratings


Operating Temperature	-55°C to 100°C		
Storage Temperature	-55°C to 100°C		
RF Power Input*	10W max at 25°C		


^{*} Passband rating, derate linearly to 3.5W at 100°C ambient Permanent damage may occur if any of these limits are exceeded

Pin Connections

RF IN	1_
RF OUT	3
GROUND	2,4

Outline Drawing






Suggested Layout, Tolerance to be within ±.002

Outline Dimensions (inch)

A .126 3.20	B .063 1.60	C .037 0.94	.020 0.51	E .032 0.81	F .009 0.23	G .169 4.29		
Н	J	K	L	М	N	Р	wt	
.087	.024	.122	.024	.087	.012	.071	grams	
2.21	0.61	3.10	0.61	2.21	0.30	1.80	.020	

Demo Board MCL P/N: TB-270 Suggested PCB Layout (PL-137)



COPLANAR WAYEGUIDE PARAMETERS ARE SHOWN FOR ROGERS ROA\$50B WITH THICKNESS .020" ± .0015". COPPER: 1/2 02. EACH SIDE. FOR OTHER MATERIALS TRACE WIDTH & GAP MAY NEED TO BE MODIFIED. NOTES: 1.

DENOTES DESCRIPTION OF THE PCB IS CONTINUOUS GROUND PLANE.

DENOTES PCB COPPER LAYOUT WITH SMOBC (SOLDER MASK OVER BARE COPPER)

DENOTES COPPER LAND PATTERN FREE OF SOLDER MASK

Features

- · excellent power handling, 10W
- small size
- 7 sections
- temperature stable
- LTCC construction
- protected by U.S. Patent 6,943,646

Applications

- harmonic rejection
- VHF/UHF transmitters/receivers
- lab use


Electrical Specifications(1,2) at 25°C

Pa	rameter	F#	Frequency (MHz)	Min.	Тур.	Max.	Unit
	Insertion Loss	DC-F1	DC-2750	_	_	1.0	dB
Pass Band	Freq. Cut-Off	F2	3150	_	3.0	_	dB
	VSWR	DC-F1	DC-2750	_	1.2	_	:1
		F3	4000	20	_	_	dB
Stop Band	Rejection Loss	F4-F5	4100-6800	_	30	_	dB
Stop Ballu		F6	8400	_	20	_	dB
	VSWR	F3-F6	4000-8400	_	20	_	:1

(1) In Applications where DC isolation to ground is required, coupling capacitors are recommended to avoid DC leakage. Alternatively, if DC pass IN-OUT is required, Mini-Circuits' "D" suffix version of this model will support DC IN-OUT, and provide>100 MOhm isolation to ground. (2) Measured on Mini-Circuits Characterization Test Board TB-270.


Typical Frequency Response ATTENUATION F1 F2 F3 F4 FREQUENCY






Typical Performance Data at 25°C

Frequency (MHz)	Insertion Loss (dB)	VSWR (:1)
1.00	0.08	1.02
500.00	0.18	1.04
1300.00	0.33	1.10
2100.00	0.51	1.25
2750.00	0.86	1.35
3150.00	2.97	2.69
3775.00	24.29	75.53
3900.00	30.94	72.39
4400.00	44.62	41.37
5600.00	36.47	56.04
6400.00	34.65	43.44
6800.00	30.90	33.42
7800.00	24.29	24.48
8400.00	20.96	22.29
9000.00	17.89	18.30





Notes
A. Performance and quality attributes and conditions not expressly stated in this specification document are intended to be excluded and do not form a part of this specification document.
B. Electrical specifications and performance data contained in this specification document are based on Mini-Circuit's applicable established test performance criteria and measurement instructions.
C. The parts covered by this specification document are subject to Mini-Circuits standard limited warranty and terms and conditions (collectively, "Standard Terms"); Purchasers of this part are entitled to the rights and benefits contained therein. For a full statement of the Standard Terms and the exclusive rights and remedies thereunder, please visit Mini-Circuits' website at www.minicircuits.com/MCLStore/terms.jsp