Type-N/BNC Adaptenuator


DC to 2000 MHz 50Ω 0.5W 6dB

Maximum Ratings

Operating Temperature -55°C to 100°C Storage Temperature -55°C to 150°C

Permanent damage may occur if any of these limits are exceeded.


Outline Drawing



Outline Dimensions (inch)

wt	D	В
grams	2.00	.73
48.2	50.80	18.54

Electrical Schematic



Features

- improved interface matching
- wideband, DC to 2000 MHz, useable to 4000 MHz
- excellent VSWR, 1.1:1 typ.
- excellent flatness, ±0.1dB typ.
- rugged unibody construction

NF-BM-6



CASE STYLE: DJ867

Connectors		Model
Conn1	Conn2	
N-Female	BNC-Male	NF-BM-6

Applications

- instrumentation
- · provides attenuation and connector type change
- minimizes hardware


Electrical Specifications


FREQ. (MHz)	ATTENUATION (dB) VSWR (:1) Flatness*							MAX. INPUT						
MHz			C-1000 DC-2000 MHz MHz		DC-500 DC-1000 MHz MHz			DC-2000 MHz		POWER (W)				
f _L -f _U	Nom.	Тур.	Max.	Тур.	Max.	Тур.	Max.	Тур.	Max.	Тур.	Max.	Тур.	Max.	
DC-2000	6±0.3	0.05	0.15	0.10	0.20	0.15	0.25	1.1	1.2	1.1	1.2	1.2	1.25	0.5

^{*}Flatness defined as peak to peak attenuation over band divided by 2.

Typical Performance Data

FREQUENCY (MHz)	ATTENUATION (dB)		WR 1)	
		BNC-Male	N-Female	
1.00	5.99	1.00	1.00	
5.00	5.99	1.00	1.00	
10.00	5.98	1.00	1.00	
50.00	5.98	1.00	1.01	
100.00	6.00	1.01	1.01	
500.00	6.04	1.03	1.04	
1000.00	6.07	1.06	1.06	
1500.00	6.12	1.07	1.06	
1700.00	6.14	1.05	1.07	
2000.00	6.18	1.03	1.08	





- A. Performance and quality attributes and conditions not expressly stated in this specification document are intended to be excluded and do not form a part of this specification document.

 B. Electrical specifications and performance data contained in this specification document are based on Mini-Circuit's applicable established test performance criteria and measurement ins.

 C. The parts covered by this specification document are subject to Mini-Circuits standard limited warranty and terms and conditions (collectively: "Standard Terms"): Purchases of this part. Ferrormance and updany attributes and contained in this specification document are based on Mini-Circuit's applicable established test performance criteria and measurement instructions. The parts covered by this specification document are subject to Mini-Circuits standard limited warranty and terms and conditions (collectively, "Standard Terms"); Purchasers of this part are entitled to the rights and benefits contained therein. For a full statement of the Standard Terms and the exclusive rights and remedies thereunder, please visit Mini-Circuits' website at www.minicircuits.com/MCLStore/terms.jsp