RF Transformer

TC3-1T

50Q

5 to 300 MHz

Maximum Ratings

Operating Temperature	-20°C to 85°C		
Storage Temperature	-55°C to 100°C		
RF Power	0.25W		
DC Current	30mA		
Permanent damage may occur if any of these limits are exceeded.			

Pin Connections

PRIMARY DOT	6
PRIMARY	4
SECONDARY DOT	1
SECONDARY	3
SECONDARY CT	2


Features

- excellent amplitude unbalance (0.3 dB typ) and phase unbalance (5 deg. typ) in 1 dB bandwidth
- · leadless surface mount

CASE STYLE: AT224 PRICE: Contact Sales Dept.

PRIMARY DOT	<u> </u>
PRIMARY	4
SECONDARY DOT	1
SECONDARY	3
SECONDARY CT	2

Outline Drawing AT224







Suggested Layout, Tolerance to be within ±.002

- · good return loss
- aqueous washable

Applications

- impedance matching
- balanced antennas

Transformer Electrical Specifications

Ω	FREQUENCY			
RATIO (Secondary/Primary)	(MHz)	3 dB MHz	2 dB MHz	1 dB MHz
3	5-300	_	_	5-300


NON-CATALOG


Outline Dimensions (inch)


A .150 3.81	B .150 3.81	C .150 3.81	D .050 1.27	.030 0.76	F .025 0.64
G .028 0.71	H .065 1.65	J .190 4.83	.030 0.76		wt grams 0.10

Typical Performance Data

FREQUENCY (MHz)	INSERTION LOSS (dB)	INPUT R. LOSS (dB)	
3.00	0.53	21.45	
7.00	0.45	24.23	
10.00	0.44	24.89	
50.00	0.49	24.99	
90.00	0.52	24.79	
100.00	0.53	24.74	
150.00	0.57	24.15	
200.00	0.60	23.65	
250.00	0.60	22.64	
300.00	0.66	21.73	







For detailed performance specs

^{*} Insertion Loss is referenced to mid-band loss, 0.4 dB typ.