# **RF Transformer**

CASE STYLE: AT224

PRICE: Contact Sales Dept.

# 50Q

# 200 to 1400 MHz

### **Maximum Ratings**


Operating Temperature	-20°C to 85°C
Storage Temperature	-55°C to 100°C
RF Power	0.25W
DC Current	30m <i>A</i>

Permanent damage may occur if any of these limits are exceeded.

### **Pin Connections**

6
4
3
1
2

# **Outline Drawing AT224**








Suggested Layout, Tolerance to be within ±.002

### Outline Dimensions (inch)

Α	В	С	D	Е	F
.150	.150	.150	.050	.030	.025
3.81	3.81	3.81	1.27	0.76	0.64
G	Н	J	K		wt
.028	.065	.190	.030		grams
0.71	1.65	4.83	0.76		0.10



#### **Features**

- · good return loss
- wideband, 200 to 1400 MHz
- · leadless surface mount
- · aqueous washable

# **Applications**

- push-pill amplifiers
- impedance matching

## Transformer Electrical Specifications


Ω <b>RATIO</b> (Secondary/Primary)	FREQUENCY	_	INSERTION LOSS*	
	(MHz)	3 dB MHz	2 dB MHz	1 dB MHz
4	200-1400	200-1400	300-1300	800-1100


\* Insertion Loss is referenced to mid-band loss, 0.7 dB typ.

# **NON-CATALOG**

#### **Typical Performance Data**

FREQUENCY (MHz)	INSERTION LOSS (dB)	INPUT R. LOSS (dB)	
200.00	1.33	6.74	
210.00	1.26	6.88	
300.00	1.22	8.07	
550.00	0.92	9.54	
800.00	0.88	10.68	
950.00	0.82	13.05	
1100.00	0.70	21.93	
1300.00	1.53	10.04	
1350.00	1.77	7.15	
1400.00	2.77	5.05	





For detailed performance specs

P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 Fax (718) 332-4661 The Design Engineers Search Engine Provides ACTUAL Data Instantly at minicipcuits.com