

Typical Performance Data

FREQ.	INSERTION LOSS	SMP MALE RETURN LOSS IN	SMA MALE RETURN LOSS OUT
(GHz)	(dB)	(dB)	(dB)
0.0	0.01	52.66	50.90
0.4	0.04	47.95	45.14
0.6	0.05	44.75	48.53
1.0	0.07	52.00	47.87
1.4	0.09	45.09	39.86
1.6	0.09	38.34	37.88
2.0	0.10	39.65	39.50
2.4	0.12	38.15	36.93
2.6	0.12	32.73	31.88
3.0	0.13	31.60	31.51
3.4	0.14	31.29	31.52
3.6	0.15	27.23	26.38
4.0	0.16	25.69	25.21
4.4	0.17	24.79	24.71
4.6	0.17	29.04	28.56
5.0	0.18	27.05	26.87
5.4	0.19	25.81	25.36
5.6	0.19	28.17	29.62
6.0	0.20	30.52	32.30