

*Typical Performance Data*

FREQ.	INSERTION LOSS	SMP MALE RETURN LOSS IN	SMA MALE RETURN LOSS OUT
(GHz)	(dB)	(dB)	(dB)
0.0	0.02	52.66	50.90
0.4	0.11	47.95	45.14
0.6	0.13	44.75	48.53
1.0	0.18	52.00	47.87
1.4	0.21	45.09	39.86
1.6	0.23	38.34	37.88
2.0	0.26	39.65	39.50
2.4	0.29	38.15	36.93
2.6	0.30	32.73	31.88
3.0	0.33	31.60	31.51
3.4	0.36	31.29	31.52
3.6	0.37	27.23	26.38
4.0	0.39	25.69	25.21
4.4	0.42	24.79	24.71
4.6	0.43	29.04	28.56
5.0	0.45	27.05	26.87
5.4	0.47	25.81	25.36
5.6	0.48	28.17	29.62
6.0	0.50	30.52	32.30