

Typical Performance Data

FREQ.	INSERTION LOSS	SMA MALE RETURN LOSS IN	SMA MALE RETURN LOSS OUT
(GHz)	(dB)	(dB)	(dB)
0	0.01	46.07	47.49
1	0.06	45.33	47.43
2	0.09	42.45	42.34
3	0.12	41.19	42.54
4	0.14	39.10	38.42
5	0.15	40.00	38.92
6	0.17	38.85	39.04
7	0.19	36.83	37.91
8	0.20	34.45	35.16
9	0.21	35.41	35.63
10	0.23	27.01	27.14
11	0.24	25.01	25.26
12	0.25	28.73	29.81
13	0.27	32.49	33.72
14	0.28	35.13	34.95
15	0.29	32.15	33.02
16	0.30	26.89	27.73
17	0.31	24.58	25.74
18	0.32	26.26	27.20

