

Non-Magnetic Flex Cable SMA Male to SMA Male

86N-30CSM

Typical Performance Data

FREQ.	INSERTION LOSS	SMA MALE RETURN LOSS IN	SMA MALE RETURN LOSS OUT
(GHz)	(dB)	(dB)	(dB)
0	0.02	46.07	47.49
1	0.19	45.33	47.43
2	0.28	42.45	42.34
3	0.35	41.19	42.54
4	0.41	39.10	38.42
5	0.46	40.00	38.92
6	0.51	38.85	39.04
7	0.56	36.83	37.91
8	0.60	34.45	35.16
9	0.64	35.41	35.63
10	0.69	27.01	27.14
11	0.72	25.01	25.26
12	0.76	28.73	29.81
13	0.80	32.49	33.72
14	0.84	35.13	34.95
15	0.87	32.15	33.02
16	0.91	26.89	27.73
17	0.94	24.58	25.74
18	0.97	26.26	27.20

