

Typical Performance Data

FREQ.	INSERTION LOSS	SSMP MALE RETURN LOSS IN	SMA MALE RETURN LOSS OUT
(GHz)	(dB)	(dB)	(dB)
0	0.02	49.30	48.97
1	0.19	42.16	45.75
2	0.28	33.86	34.46
3	0.35	31.49	31.78
4	0.41	36.46	38.43
5	0.46	33.10	31.46
6	0.51	27.16	26.83
7	0.56	26.40	28.89
8	0.60	26.99	26.28
9	0.64	28.12	28.11
10	0.69	38.71	38.01
11	0.72	27.72	35.04
12	0.76	28.01	28.85
13	0.80	30.52	31.22
14	0.84	29.90	37.01
15	0.87	33.10	35.73
16	0.91	29.57	30.96
17	0.94	22.99	24.21
18	0.97	21.76	23.29

