

*Typical Performance Data*

FREQ.	INSERTION LOSS	SSMP MALE RETURN LOSS IN	SMA MALE RETURN LOSS OUT
(GHz)	(dB)	(dB)	(dB)
0	0.03	49.30	48.97
1	0.32	42.16	45.75
2	0.46	33.86	34.46
3	0.58	31.49	31.78
4	0.68	36.46	38.43
5	0.77	33.10	31.46
6	0.85	27.16	26.83
7	0.93	26.40	28.89
8	1.00	26.99	26.28
9	1.07	28.12	28.11
10	1.14	38.71	38.01
11	1.21	27.72	35.04
12	1.27	28.01	28.85
13	1.33	30.52	31.22
14	1.39	29.90	37.01
15	1.45	33.10	35.73
16	1.51	29.57	30.96
17	1.57	22.99	24.21
18	1.62	21.76	23.29

