

Typical Performance Data

| FREQUENCY (MHz) | AVERAGE INSERTION LOSS (dB) | INPUT RETURN LOSS (dB) | AMPLITUDE UNBALANCE (dB) | PHASE UNBALANCE (deg) |
|--------------------|--------------------------------------|---------------------------------|--------------------------------|-----------------------------|
| 0.03 | 0.17 | 16.36 | 0.01 | 0.06 |
| 0.05 | 0.08 | 20.69 | 0.00 | 0.04 |
| 0.10 | 0.06 | 26.79 | 0.00 | 0.01 |
| 0.50 | 0.07 | 38.06 | 0.00 | 0.02 |
| 1.00 | 0.06 | 39.09 | 0.00 | 0.03 |
| 5.00 | 0.07 | 32.08 | 0.00 | 0.10 |
| 10.00 | 0.11 | 27.04 | 0.01 | 0.19 |
| 50.00 | 0.42 | 14.63 | 0.13 | 0.89 |
| 100.00 | 1.16 | 9.25 | 0.52 | 1.93 |
| 125.00 | 1.58 | 7.66 | 0.83 | 2.58 |