

## Typical Performance Data

FREQUENCY (MHz)	AVERAGE INSERTION LOSS (dB)	INPUT RETURN LOSS (dB)	AMPLITUDE UNBALANCE (dB)	PHASE UNBALANCE (deg)
1	1.20	13.07	0.03	0.05
2	0.95	14.28	0.02	0.05
4	0.84	14.97	0.02	0.02
10	0.81	15.21	0.02	0.07
40	0.87	14.68	0.02	0.27
100	0.96	12.96	0.02	0.78
120	0.95	12.27	0.02	0.93
150	1.00	11.19	0.01	1.19
200	1.32	9.52	0.00	1.71
250	1.26	8.05	0.03	2.32