

# Fixed Attenuator

# BW-S3W10+

## Typical Performance Data

FREQUENCY (MHz)	ATTENUATION (dB)	VSWR (:1)
0.3	2.76	1.08
10	2.76	1.09
50	2.78	1.08
100	2.79	1.08
200	2.80	1.08
300	2.80	1.08
400	2.81	1.08
500	2.82	1.08
600	2.83	1.08
700	2.84	1.08
800	2.85	1.08
900	2.85	1.08
1000	2.86	1.08
1100	2.87	1.08
1200	2.87	1.08
1300	2.88	1.08
1400	2.88	1.08
1500	2.88	1.08
1600	2.88	1.08
1700	2.89	1.08
1800	2.89	1.08
1900	2.89	1.08
2000	2.90	1.08
2100	2.90	1.08
2200	2.91	1.08
2300	2.91	1.08
2400	2.91	1.08
2500	2.91	1.09
2600	2.92	1.09
2700	2.92	1.09
2800	2.92	1.09
2900	2.93	1.10
3000	2.93	1.10
3500	2.94	1.11
4000	2.96	1.12
4500	2.97	1.11
5000	2.98	1.09
5500	3.00	1.06
6000	3.01	1.05
6500	3.03	1.07
7000	3.05	1.09
7500	3.08	1.11
8000	3.10	1.15
8500	3.13	1.17
9000	3.16	1.17
9500	3.18	1.14
10000	3.20	1.08
10500	3.23	1.02
11000	3.24	1.05
11500	3.26	1.08
12000	3.26	1.07
12400	3.30	1.04