

Typical Performance Data

FREQ.	INSERTION LOSS	SMA MALE RETURN LOSS IN	SMA MALE RETURN LOSS OUT
(GHz)	(dB)	(dB)	(dB)
0	0.12	44.90	45.79
1	0.24	34.99	34.82
2	0.34	35.24	35.06
3	0.40	38.37	37.68
4	0.46	43.35	40.80
5	0.51	45.09	42.07
6	0.56	39.67	38.97
7	0.60	35.78	36.57
8	0.65	33.71	33.30
9	0.69	31.13	30.41
10	0.73	30.15	30.02
11	0.76	30.84	31.15
12	0.80	34.62	35.44
13	0.83	38.57	38.26
14	0.87	40.31	37.61
15	0.90	35.16	34.05
16	0.94	30.73	30.32
17	0.97	28.33	28.49
18	1.00	27.77	28.73
19	1.03	29.52	30.48
20	1.06	33.29	32.85
21	1.09	34.77	36.30
22	1.12	34.50	34.58
23	1.15	33.28	33.47
24	1.18	30.15	29.90
25	1.21	27.94	29.10
26	1.24	27.97	29.46
27	1.26	30.11	30.09