

Coaxial Fixed Attenuator

FW-1A+

Typical Performance Data

FREQ.	ATTENUATION	VSWR
(MHz)	(dB)	(:1)
10	0.96	1.08
20	0.96	1.08
50	0.96	1.08
100	0.97	1.08
200	0.98	1.08
300	0.99	1.08
400	1.00	1.08
500	1.01	1.07
600	1.02	1.07
700	1.03	1.07
800	1.04	1.07
900	1.04	1.07
1000	1.05	1.07
1200	1.07	1.07
1400	1.08	1.07
1600	1.10	1.07
1800	1.11	1.07
2000	1.12	1.08
2200	1.13	1.09
2400	1.14	1.10
2600	1.15	1.11
2800	1.15	1.12
3000	1.16	1.13
3200	1.17	1.14
3400	1.17	1.14
3600	1.18	1.15
3800	1.19	1.15
4000	1.19	1.16
4200	1.19	1.16
4400	1.20	1.16
4600	1.20	1.16
4800	1.20	1.16
5000	1.21	1.16
5200	1.21	1.16
5400	1.22	1.16
5600	1.22	1.16
5800	1.23	1.16
6000	1.23	1.15
6200	1.24	1.15
6400	1.24	1.15
6600	1.25	1.14
6800	1.25	1.13
7000	1.26	1.12
7200	1.26	1.11
7400	1.27	1.10
7600	1.28	1.09
7800	1.28	1.08
8000	1.29	1.07
8200	1.29	1.06
8400	1.30	1.05
8600	1.30	1.05
8800	1.31	1.05
9000	1.32	1.06
9200	1.33	1.07
9400	1.34	1.09
9600	1.35	1.11
10000	1.37	1.14
11000	1.40	1.18
11500	1.42	1.17
12000	1.43	1.17

