


Fixed Attenuator

GAT-12+

Typical Performance Data

| FREQUENCY (GHz) | ATTENUATION (dB) | RETURN LOSS (dB) |
|--------------------|---------------------|---------------------|
| 100.0 | 11.94 | 46.06 |
| 300.0 | 12.01 | 40.09 |
| 1000.0 | 12.09 | 40.09 |
| 2000.0 | 12.18 | 36.61 |
| 3000.0 | 12.24 | 30.71 |
| 4000.0 | 12.41 | 27.32 |
| 5000.0 | 12.53 | 24.94 |
| 6000.0 | 12.56 | 22.12 |
| 7000.0 | 13.03 | 20.08 |
| 8000.0 | 13.11 | 17.69 |



P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 • Fax (718) 332-4661 For detailed performance specs & shopping online see Mini-Circuits web site
 The Design Engineers Search Engine Provides ACTUAL Data Instantly From MINI-CIRCUITS At: www.minicircuits.com

IF/RF MICROWAVE COMPONENTS

REV. OR
GAT-12+
7/11/2012
Page 1 of 1