

2 Way-0° Power Splitter/Combiner

GP2-ED13012A/3

Typical Performance Data

FREQUENCY (MHz)	TOTAL LOSS ¹ (dB)		AMPLITUDE UNBALANCE (dB)	ISOLATION (dB)	PHASE UNBALANCE (Deg)	FREQUENCY (MHz)	VSWR (:1)		
	S-1	S-2					S	1	2
2560.0	4.66	4.75	0.10	11.11	2.45	2560.0	2.06	1.28	1.23
2630.0	4.35	4.43	0.08	13.37	2.33	2630.0	1.75	1.27	1.22
2690.0	4.15	4.23	0.08	15.32	2.30	2690.0	1.54	1.24	1.20
2760.0	3.98	4.05	0.07	17.66	2.33	2760.0	1.35	1.20	1.16
2830.0	3.86	3.92	0.06	19.96	2.37	2830.0	1.20	1.17	1.13
2900.0	3.78	3.84	0.06	22.02	2.44	2900.0	1.08	1.14	1.11
3000.0	3.71	3.77	0.06	23.54	2.53	3000.0	1.07	1.13	1.10
3180.0	3.66	3.71	0.05	22.58	2.72	3180.0	1.23	1.14	1.12
3360.0	3.64	3.68	0.04	21.14	2.92	3360.0	1.33	1.16	1.13
3540.0	3.61	3.64	0.03	20.67	3.08	3540.0	1.36	1.15	1.11
3720.0	3.57	3.59	0.03	20.82	3.20	3720.0	1.34	1.14	1.08
3900.0	3.52	3.55	0.02	21.57	3.30	3900.0	1.28	1.12	1.04
4080.0	3.48	3.52	0.03	22.89	3.42	4080.0	1.20	1.09	1.01
4270.0	3.46	3.49	0.04	25.19	3.58	4270.0	1.12	1.05	1.06
4450.0	3.44	3.49	0.04	29.16	3.77	4450.0	1.09	1.01	1.11
4630.0	3.45	3.49	0.04	38.44	3.97	4630.0	1.13	1.05	1.15
4810.0	3.47	3.51	0.03	37.75	4.17	4810.0	1.21	1.09	1.19
4990.0	3.51	3.53	0.02	28.55	4.38	4990.0	1.29	1.13	1.22
5170.0	3.55	3.56	0.01	24.69	4.58	5170.0	1.36	1.16	1.22
5360.0	3.58	3.59	0.01	22.40	4.75	5360.0	1.41	1.18	1.21
5540.0	3.61	3.62	0.01	20.83	4.94	5540.0	1.45	1.18	1.18
5720.0	3.62	3.64	0.03	19.75	5.14	5720.0	1.45	1.17	1.13
5900.0	3.61	3.66	0.05	18.68	5.49	5900.0	1.45	1.16	1.09
6080.0	3.60	3.65	0.05	17.77	5.73	6080.0	1.43	1.13	1.05
6260.0	3.59	3.65	0.05	17.10	6.01	6260.0	1.40	1.10	1.05
6450.0	3.58	3.64	0.06	16.51	6.22	6450.0	1.36	1.05	1.09
6600.0	3.57	3.63	0.06	16.13	6.37	6600.0	1.33	1.03	1.14
7470.0	3.69	3.73	0.04	13.51	7.31	7470.0	1.27	1.40	1.38
8350.0	4.24	3.88	0.36	10.27	10.71	8350.0	1.44	1.76	1.51
10110.0	3.74	5.11	1.37	17.38	12.66	10110.0	1.36	1.22	1.41

¹Total Loss = Insertion Loss + 3dB Splitter Loss



P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 • Fax (718) 332-4661 For detailed performance specs & shopping online see Mini-Circuits web site
 The Design Engineers Search Engine Provides ACTUAL Data Instantly From MINI-CIRCUITS At: www.minicircuits.com

IF/RF MICROWAVE COMPONENTS

REV. X2
 GP2-ED13012A/3
 8/25/2010
 Page 1 of 1