

# 6 Way-0° Power Splitter/Combiner

# ZB6PD-2+

## Typical Performance Data

FREQ. (MHz)	INSERTION LOSS (dB)	AMP. UNBAL. (dB)	ISOLATION (dB)		FREQ. (MHz)	VSWR (:1)	
			Adjacent	Opposite		S	OUTPUTS
801.5	8.47	0.33	39.60	23.12	801.5	1.15	1.21
887.0	8.49	0.31	32.26	24.98	887.0	1.12	1.19
986.5	8.54	0.33	27.48	26.44	986.5	1.21	1.18
1085.0	8.52	0.31	26.40	28.83	1085.0	1.18	1.17
1179.5	8.53	0.31	25.53	31.14	1179.5	1.03	1.11
1278.5	8.60	0.31	22.70	28.45	1278.5	1.21	1.07
1377.5	8.61	0.30	22.46	26.13	1377.5	1.31	1.12
1472.0	8.66	0.30	26.27	26.38	1472.0	1.25	1.15
1571.0	8.69	0.27	38.21	32.21	1571.0	1.19	1.15
1665.0	8.71	0.26	38.95	29.48	1665.0	1.19	1.11
1764.5	8.77	0.33	31.36	27.36	1764.5	1.21	1.06
1863.5	8.84	0.30	29.93	27.81	1863.5	1.22	1.07
1913.0	8.89	0.32	28.17	27.62	1913.0	1.23	1.07
1958.0	8.97	0.34	24.73	25.52	1958.0	1.24	1.07
1998.5	9.01	0.35	21.70	23.15	1998.5	1.25	1.07