

6 Way-0° Power Splitter/Combiner

ZB6PD-2+

Typical Performance Data

FREQ. (MHz)	INSERTION LOSS (dB)	AMP. UNBAL. (dB)	ISOLATION (dB)		FREQ. (MHz)	VSWR (:1)	
			Adjacent	Opposite		S	OUTPUTS
801.5	8.47	0.33	39.60	23.12	801.5	1.15	1.21
887.0	8.49	0.31	32.26	24.98	887.0	1.12	1.19
986.5	8.54	0.33	27.48	26.44	986.5	1.21	1.18
1085.0	8.52	0.31	26.40	28.83	1085.0	1.18	1.17
1179.5	8.53	0.31	25.53	31.14	1179.5	1.03	1.11
1278.5	8.60	0.31	22.70	28.45	1278.5	1.21	1.07
1377.5	8.61	0.30	22.46	26.13	1377.5	1.31	1.12
1472.0	8.66	0.30	26.27	26.38	1472.0	1.25	1.15
1571.0	8.69	0.27	38.21	32.21	1571.0	1.19	1.15
1665.0	8.71	0.26	38.95	29.48	1665.0	1.19	1.11
1764.5	8.77	0.33	31.36	27.36	1764.5	1.21	1.06
1863.5	8.84	0.30	29.93	27.81	1863.5	1.22	1.07
1913.0	8.89	0.32	28.17	27.62	1913.0	1.23	1.07
1958.0	8.97	0.34	24.73	25.52	1958.0	1.24	1.07
1998.5	9.01	0.35	21.70	23.15	1998.5	1.25	1.07