## Engineering Development Model

## **Frequency Mixer**

## **ADE-ED6820**

Level 7 (LO Power +7 dBm)

## **Important Note**

This model has been designed, built and tested in our engineering department. Performance data represents model capability. At present it is a non-catalog model. On request, we can supply a final specification sheet, part number and price/delivery information.



Please click "Back", and then click "Contact Us" for Applications support.

**CASE STYLE: CD542** 

	ELECTRICAL	L SPECIFICATION	IS 50Ω @ +25°0		
Parameter		Min.	Тур.	Max.	Units
Frequency	LO (fL to fU)	5		1200	MHz
	<b>RF</b> (f∟ to f∪)	5		1200	MHz
	IF	10		920	MHz
Conversion Loss	mid band		6.8		dB
	<b>Total Range</b>		6.8		dB
LO-RF Isolation	Low Range		58		dB
	Mid Range		41		dB
	<b>Upper Range</b>		36		dB
LO-IF Isolation	Low Range		57		dB
	Mid Range		41		dB
	<b>Upper Range</b>		27		dB

Note: Low Range = [fL to 10fL] mid band = [2fL to fU/2] Mid Range = [10fL to fU/2]

Upper Range = [fu/2 to fu]

MAXIMUM RATINGS			
Operating Temperature	-40°C to 85°C		
Storage Temperature	-55°C to 100°C		

PIN CONNECTIONS			
LO	3		
RF	1		
IF	4		
GROUND	2, 5, 6		