## Engineering Development Model

## **Frequency Mixer**

## HJK-ED9468/2

Level 7 (LO Power +7 dBm)

## **Important Note**

This model has been designed, built and tested in our engineering department. Performance data represents model capability. At present it is a non-catalog model. On request, we can supply a final specification sheet, part number and price/delivery information.



Please click "Back", and then click "Contact Us" for Applications support.

**CASE STYLE: TTT166** 

| ELECTRICAL SPECIFICATIONS 50Ω @ +25°C |                      |      |      |      |       |
|---------------------------------------|----------------------|------|------|------|-------|
| Parameter                             |                      | Min. | Тур. | Max. | Units |
| Frequency                             | LO (fL to fU)        | 1511 |      | 1888 | MHz   |
|                                       | <b>RF</b> (f∟ to f∪) | 1511 |      | 1888 | MHz   |
|                                       | IF                   | 50   |      | 325  | MHz   |
| Conversion Loss                       |                      |      | 7.7  |      | dB    |
| LO-RF Isolation                       |                      |      | 34   |      | dB    |
| LO-IF Isolation                       |                      |      | 30   |      | dB    |
| IP3 Input                             |                      |      | +20  |      | dBm   |

| MAXIMUM RATINGS       |                |  |  |
|-----------------------|----------------|--|--|
| Operating Temperature | -40°C to 85°C  |  |  |
| Storage Temperature   | -55°C to 100°C |  |  |

| PIN CONNECTIONS |         |  |  |
|-----------------|---------|--|--|
| LO              | 2       |  |  |
| RF              | 1       |  |  |
| IF              | 3       |  |  |
| GROUND          | 4, 5, 6 |  |  |