## **Frequency Mixer**

## LAVI-ED12787/1D

Level 20 (LO Power + 20 dBm)

## **Important Note**

This model has been designed, built and tested in our engineering department. Performance data represents model capability. At present it is a non-catalog model. On request, we can supply a final specification sheet, part number and price/delivery information.



Please click "Back", and then click "Contact Us" for Applications support.

**CASE STYLE: CK605** 

ELECTRICAL SPECIFICATIONS 50Ω @ +25°C						
Parameter		Min.	Тур.	Max.	Units	
Frequency	LO (fL to fu)	1270		2500	MHz	
	<b>RF</b> (f∟ to f∪)	1270		2500	MHz	
	IF	170		230	MHz	
Conversion Loss	Total Range		8.2		dB	
LO-RF Isolation			50		dB	
LO-IF Isolation			43		dB	
Input IP3			+27		dBm	
1 dB Compression			+17		dBm	

MAXIMUM RATINGS		
Operating Temperature	-45°C to 85°C	
Storage Temperature	-55°C to +100°C	

PIN CONNECTIONS				
LO	10			
RF	2			
IF	14			
GROUND	1,3,4,5,6,7,8,9,11,12,13,15,16			

## **Electrical Schematic**

