## Engineering Development Model

## **Frequency Mixer**

## LRMS-ED6552/1

Level 7 (LO Power + 7 dBm)

## **Important Note**

This model has been designed, built and tested in our engineering department. Performance data represents model capability. At present it is a non-catalog model. On request, we can supply a final specification sheet, part number and price/delivery information.



Please click "Back", and then click "Contact Us" for Applications support.

**CASE STYLE: QQQ569** 

ELECTRICAL SPECIFICATIONS 50Ω @ +25°C						
Parameter		Min.	Тур.	Max.	Units	
Frequency	<b>LO</b> (f∟ to f∪)	10		1000	MHz	
	<b>RF</b> (f∟ to f∪)	10		1000	MHz	
	IF	10		490	MHz	
Conversion Loss	mid band		6.3		dB	
	Total Range		6.8		dB	
LO-RF Isolation	Low Range		49		dB	
	Mid Range		38		dB	
	<b>Upper Range</b>		33		dB	
LO-IF Isolation	Low Range		44		dB	
	Mid Range		33		dB	
	<b>Upper Range</b>		25		dB	
Input IP3			+16		dBm	
1 dB Compression			+1		dBm	

**Note:** Low Range = [fL to 10fL] mid band = [2fL to fU/2]

Mid Range = [10fL to fU/2]

Upper Range = [fu/2 to fu]

MAXIMUM RATINGS		
Operating Temperature	-40°C to +85°C	
Storage Temperature	-55°C to +100°C	

PIN CONNECTIONS			
LO	1		
RF	4		
IF	5		
GROUND	2,3,6		



