# Engineering Development Model

# **RF Transformer**

### TCM-ED8064/1

Impedance Ratio: 4

#### **Important Note**

This model has been designed, built and tested in our engineering department. Performance data represents model capability. At present it is a non-catalog model. On request, we can supply a final specification sheet, part number and price/delivery information.



Please click "Back", and then click "Contact Us" for Applications support.

**CASE STYLE: DB714** 

ELECTRICAL SPECIFICATIONS 75Ω @ +25°C					
Parameter		Min.	Тур.	Max.	Units
Frequency		0.5		350	MHz
Insertion Loss *	3 dB Bandwidth		0.5 - 350		MHz
	2 dB Bandwidth		0.5 - 300		MHz
	1 dB Bandwidth		0.5 - 175		MHz
Ampitude Unbalance	over 3dB Bandwidth		0.5		dB
	over 1dB Bandwidth		0.1		dB
Phase Unbalance	over 3dB Bandwidth		5.0		deg.
	over 1dB Bandwidth		1.00		deg.

#### Note:

<sup>\*</sup> Insertion Loss is referenced to mid-band loss, 0.24dB typ.

MAXIMUM RATINGS			
Operating Temperature	-20°C to 85°C		
Storage Temperature	-55°C to 100°C		
RF Power	0.25 W		
DC Current	30 mA		

PIN CONNECTIONS			
PRIMARY DOT	1		
PRIMARY	3		
SECONDARY DOT	6		
SECONDARY	4		
SECONDARY CT	5		
ISOLATE	2		

### **Configuration: A**

