RF Transformer

TCM9-1



CASE STYLE: DB714 PRICE: Contact Sales Dept.

50Ω 2 to 280 MHz


Maximum Ratings

Operating Temperature	-20°C to 85°C
Storage Temperature	-55°C to 100°C
RF Power	0.25W
DC Current	30mA
Permanent damage may occur if any	of these limits are exceeded.


Pin Connections

PRIMARY DOT	6
PRIMARY	4
SECONDARY DOT	1
SECONDARY	3
SECONDARY CT	2
NOT USED	5

Outline Drawing



PCB Land Pattern




Suggested Layout, Tolerance to be within ± 002

Outline Dimensions (inch)

Α	В	С	D	Ε	F
.160	.150	.160	.050	.040	.025
4.06	3.81	4.06	1.27	1.02	0.64
G	Н	J	K		wt
G .028	H .065	J .190	K .030		wt grams

Config. A



Features

- excellent amplitude unbalance, 0.15 dB typ. and phase unbalance, 1 deg typ. in 1 dB bandwidth
- plastic base with solder plated leads
- aqueous washable

Applications

- impedance matching
- balanced to unbalanced transformation

Transformer Electrical Specifications


Ω RATIO (Secondary/Prir	FREQUENCY (MHz)	3 dB MHz	INSERTION LOSS* 2 dB MHz	1 dB MHz
9	2-280	2-280	3-150	5-100

^{*} Insertion Loss is referenced to mid-band loss, 0.9 dB typ

Typical Performance Data

FREQUENCY (MHz)	INSERTION LOSS (dB)	INPUT R. LOSS (dB)	
2	1.09	13.99	
5	0.87	15.12	
10	0.82	15.35	
30	0.87	15.03	
50	0.90	14.41	
100	1.05	12.56	
150	1.36	10.70	
200	1.43	9.02	
250	2.01	7.65	
280	2.11	6.95	







For detailed performance specs & shopping online see web site

