## **Frequency Mixer**

## TUF-3SM+

## Level 7 (LO Power +7 dBm) 0.15 to 400 MHz

#### **Maximum Ratings**


| Operating Temperature | -55°C to 100°C |
|-----------------------|----------------|
| Storage Temperature   | -55°C to 100°C |
| RF Power              | 50mW           |
| IF Current            | 40mA           |


Permanent damage may occur if any of these limits are exceeded

#### **Pin Connections**

| LO          | 4 |
|-------------|---|
| RF          | 1 |
| IF          | 2 |
| GROUND      | 3 |
| CASE GROUND | 3 |

### **Outline Drawing**






Tolerance to be within ±.002

#### Outline Dimensions (inch )

| G     | F    | Е    | D    | С    | В     | Α     |
|-------|------|------|------|------|-------|-------|
| .06   | .21  | .23  | .240 | .255 | .48   | .50   |
| 1.52  | 5.33 | 5.84 | 6.10 | 6.48 | 12.19 | 12.70 |
|       |      |      |      |      |       |       |
| wt    | N    | M    | L    | K    | J     | Н     |
| grams | .005 | .09  | .020 | .16  | .09   | .100  |
| 1.9   | 0.13 | 2.29 | 0.51 | 4.06 | 2.29  | 2.54  |

#### Demo Board MCL PIN: TB-201 Suggested PCB Layout (PL-081)



NOTES: 1.TRACE WIDTH IS SHOWN FOR ROGERS RO4350B WITH DIELECTRIC THICKNESS 0.030° ± 0.002°; COPPER: 1/2 0Z. EACH SIDE. FOR OTHER MATERIALS TRACE WIDTH MAY NEED TO BE MODIFIED.

2.BOTTOM SIDE OF THE PCB IS CONTINUOUS GROUND PLANE.

DENOTES PCB COPPER LAYOUT WITH SMOBC (SOLDER MASK OVER BARE COPPER)

DENOTES COPPER LAND PATTERN FREE OF SOLDER MASK

#### **Features**

- low conversion loss, 4.7 dB typ.
- excellent L-R isolation, 46 dB typ.; L-I, 47 dB typ.
- rugged welded construction

# Generic photo used for illustration purposes only

CASE STYLE: NNN150

+RoHS Compliant

The +Suffix identifies RoHS Compliance. See our web site for RoHS Compliance methodologies and qualifications

#### **Applications**

- HF/VHF
- defense & federal communication

#### **Electrical Specifications**

| FREQU<br>(MI                   | JENCY<br>Hz) | COI |               | SION<br>dB) | LOSS           | LO-RF ISOLATION<br>(dB) |      |      |      | LO-IF ISOLATION<br>(dB) |      |      |      |      | IP3 @<br>CENTER BAND<br>(dBm) |      |      |      |
|--------------------------------|--------------|-----|---------------|-------------|----------------|-------------------------|------|------|------|-------------------------|------|------|------|------|-------------------------------|------|------|------|
| LO/RF                          | IF           | N   | /lid-Bar<br>m | nd          | Total<br>Range | ı                       | L    | N    | M    | ι                       | J    |      | L    | N    | Л                             | ι    | J    |      |
| f <sub>L</sub> -f <sub>U</sub> |              | X   | σ             | Max.        | Max.           | Тур.                    | Min. | Тур. | Min. | Тур.                    | Min. | Тур. | Min. | Тур. | Min.                          | Тур. | Min. | Тур. |
| 0.15-400                       | DC-400       | 4.7 | 0.02          | 7.0         | 8.0            | 60                      | 50   | 46   | 30   | 35                      | 25   | 60   | 40   | 47   | 25                            | 35   | 20   | 11   |

1 dB COMP.: +1 dBm typ. For phase detection, DC positive polarity with in-phase RF & LO.


L = 50-100 MHz M = 100-500 MHz U = upper range  $[f_{ij}/2 \text{ to } f_{ij}]$ 

m= mid band  $[2f_i \text{ to } f_i/2]$ 

#### **Typical Performance Data**

|   | Frequency<br>(MHz)   |  | Conversion<br>Loss<br>(dB)   | VSWR<br>RF Port<br>(:1)  | Frequency<br>(MHz)   | Isolation<br>L-R<br>(dB)   | Isolation<br>L-I<br>(dB)   | VSWR<br>LO Port<br>(:1)  |
|---|--|--|--|--|--|--|--|--|
|   | RF   | LO   | LO<br>+7dBm  | LO<br>+7dBm  | LO   | LO<br>+7dBm  | LO<br>+7dBm  | LO<br>+7dBm  |
| - | 0.15<br>0.23<br>0.30<br>0.50<br>1.00<br>2.80<br>6.40<br>10.00<br>28.00<br>64.00                  | 30.15<br>30.23<br>30.30<br>30.50<br>31.00<br>32.80<br>36.40<br>40.00<br>58.00<br>94.00           | 5.37<br>5.27<br>5.21<br>5.16<br>5.08<br>4.91<br>4.93<br>4.73<br>4.71         | 1.57<br>1.41<br>1.33<br>1.25<br>1.21<br>1.21<br>1.21<br>1.21<br>1.21<br>1.21 | 10.00<br>20.00<br>30.00<br>40.00<br>76.00<br>94.00<br>112.00<br>149.00<br>168.00<br>206.00       | 68.68<br>65.36<br>63.22<br>61.75<br>57.56<br>56.48<br>54.90<br>52.63<br>54.13<br>49.62 | 61.84<br>56.87<br>54.20<br>52.09<br>47.59<br>45.97<br>44.70<br>42.36<br>42.02<br>38.81 | 2.59<br>2.60<br>2.59<br>2.58<br>2.54<br>2.50<br>2.50<br>2.57<br>2.55<br>2.62 |
|   | 100.00<br>138.00<br>157.00<br>195.00<br>233.00<br>252.00<br>271.00<br>290.00<br>370.00<br>400.00 | 130.00<br>168.00<br>187.00<br>225.00<br>263.00<br>282.00<br>301.00<br>320.00<br>340.00<br>370.00 | 4.83<br>4.85<br>4.88<br>4.92<br>4.97<br>5.10<br>5.17<br>5.15<br>5.38<br>5.41 | 1.14<br>1.13<br>1.10<br>1.08<br>1.10<br>1.12<br>1.14<br>1.17<br>1.10<br>1.05 | 225.00<br>244.00<br>282.00<br>301.00<br>320.00<br>340.00<br>360.00<br>390.00<br>410.00<br>430.00 | 48.10<br>48.03<br>53.65<br>55.10<br>54.03<br>52.86<br>51.53<br>47.44<br>45.39<br>44.42 | 38.56<br>37.82<br>37.79<br>38.07<br>37.59<br>36.62<br>35.44<br>33.11<br>32.24<br>32.17 | 2.66<br>2.68<br>2.67<br>2.76<br>2.82<br>2.76<br>2.69<br>2.86<br>3.05<br>3.06 |


#### **Electrical Schematic**





A. Performance and quality attributes and conditions not expressly stated in this specification document are intended to be excluded and do not form a part of this specification document.


B. Electrical specifications and performance data contained in this specification document are based on Mini-Circuit's applicable established test performance criteria and measurement instructions.


C. The parts covered by this specification document are subject to Mini-Circuit's standard limited warranty and terms and conditions (collectively, "Standard Terms"). Purchasers of this part are entitled to the rights and benefits contained therein. For a full statement of the Standard Terms and the exclusive rights and remedies thereunder, please visit Mini-Circuits' website at www.minicircuits.com/MCLStore/terms.jsp














A. Performance and quality attributes and conditions not expressly stated in this specification document are intended to be excluded and do not form a part of this specification document.

B. Electrical specifications and performance data contained in this specification document are based on Mini-Circuit's applicable established test performance criteria and measurement instructions.

C. The parts covered by this specification document are subject to Mini-Circuit's standard limited warranty and terms and conditions (collectively, "Standard Terms"); Purchasers of this part are entitled to the rights and benefits contained therein. For a full statement of the Standard Terms and the exclusive rights and remedies thereunder, please visit Mini-Circuits' website at www.minicircuits.com/WCLStore/terms.jsp