High Pass Filter

50Ω

1900 to 2700 MHz

Maximum Ratings

Operating Temperature	-55°C to 100°C
Storage Temperature	-55°C to 100°C
RF Power Input*	14W max at 25°C

^{*} Passband rating, derate linearly to 0.4x Pmax at 100°C ambient. Permanent damage may occur if any of these limits are exceeded.

Features

- rugged unibody construction, small size
- pass band insertion loss 1.0 dB typ.
- excellent power handling, 14W
- low cost

Generic photo used for illustration purposes only


CASE STYLE: FF704

Connectors	Model
SMA	VHP-16

Applications

- sub-harmonic rejection of VCO
- transmitters/receivers
- lab use

Outline Drawing




Outline Dimensions (inch)

wt	Ε	D	В
grams	.312	1.43	.410
10.0	7.92	36.32	10.41


Electrical Specifications (T_{AMB}=25°C)

	BAND Hz)	fco, MHz Nom.	PASSBAND (MHz)		WR 1)
		(loss 3 dB)		Stopband	Passband
(loss > 40 dB)	(loss > 20 dB)	Тур.	(loss < 1.3 dB)	Тур.	Typ.
DC-1030	1300	1580	1900-2700	18	1.3

typical frequency response





electrical schematic



Typical Performance Data

Frequency (MHz)	Insertion Loss (dB)	VSWR (:1)
1.00	101.37	330.92
500.00	62.34	68.33
1030.00	44.28	40.07
1300.00	23.15	24.17
1580.00	2.82	2.03
1900.00	1.12	1.27
2300.00	0.80	1.17
2700.00	1.01	1.74
3000.00	1.47	2.45
5000.00	1.03	1.97





A. Performance and quality attributes and conditions not expressly stated in this specification document are intended to be excluded and do not form a part of this specification document.

B. Electrical specifications and performance data contained in this specification document are based on Mini-Circuit's applicable established test performance criteria and measurement instructions.

C. The parts covered by this specification document are subject to Mini-Circuits standard limited warranty and terms and conditions (collectively, "Standard Terms"); Purchasers of this part are entitled to the rights and benefits contained therein. For a full statement of the Standard Terms and the exclusive rights and remedies thereunder, please visit Mini-Circuits' website at www.minicircuits.com/MCLStore/terms.jsp