Low Pass Filter

VLFX-1300+

DC to 1300 MHz (40 dB Typ. Isolation up to 20 GHz) 50Ω




Features

- Very good isolation, 40 dB typ. up to 20 GHz
- Excellent power handling, 10W
- Temperature stable LTCC internal structure
- Re-entry frequency > 20 GHz
- Protected by US patent 6,943,646
- · Rugged unibody construction


Applications

- · Harmonic rejection
- Transmitters/receivers
- Lab use
- · Test instrumentation

Functional Schematic



Typical Frequency Response



+RoHS Compliant

The +Suffix identifies RoHS Compliance. See our web site for RoHS Compliance methodologies and qualifications

Generic photo used for illustration purposes only CASE STYLE: FF1118

| Connectors | Model |
|------------|-------------|
| SMA | VI FX-1300+ |

Electrical Specifications(1) at 25°C

| Parameter F# Frequency (MHz) | | Min. | Тур. | Max. | Unit | | |
|------------------------------|------------------|-------|------------|------|------|-----|----|
| | Insertion Loss | DC-F1 | DC-1300 | _ | 1.1 | 1.6 | dB |
| Pass Band | Freq. Cut-Off | F2 | 1925 | _ | 3.0 | _ | dB |
| | VSWR | DC-F1 | DC-1300 | _ | 1.2 | _ | :1 |
| | Insertion Loss | F3 | 2300 | 20 | 26 | _ | dB |
| Stop Band | IIISEITIOII LOSS | F4-F5 | 2500-20000 | _ | 40 | _ | dB |
| | VSWR | F3-F5 | 2300-20000 | _ | 10 | _ | :1 |


(1) In Application where DC voltage is present at either input or output ports, coupling capacitors are required.


| Maximum Ratings | | | | |
|-----------------------|----------------|--|--|--|
| Operating Temperature | -55°C to 100°C | | | |
| Storage Temperature | -55°C to 100°C | | | |
| RF Power Input* | 10W max. | | | |


^{*}Passband rating, derate linearly to 3.5W at 100°C ambient. Permanent damage may occur if any of these limits are exceeded.


Typical Performance Data at 25°C

| Frequency (MHz) | Insertion Loss (dB) | VSWR (:1) |
|--------------------|------------------------|--------------|
| 10 | 0.05 | 1.02 |
| 500 | 0.41 | 1.21 |
| 1000 | 0.64 | 1.14 |
| 1300 | 0.81 | 1.05 |
| 1890 | 3.18 | 2.49 |
| 1900 | 3.41 | 2.65 |
| 1925 | 4.11 | 3.16 |
| 2050 | 10.77 | 8.51 |
| 2150 | 20.89 | 13.92 |
| 2250 | 33.74 | 16.26 |
| 2300 | 29.69 | 16.89 |
| 2500 | 42.46 | 18.50 |
| 5000 | 70.84 | 49.64 |
| 7500 | 54.28 | 36.97 |
| 10000 | 67.56 | 31.03 |
| 12500 | 67.50 | 9.08 |
| 15000 | 50.86 | 1.35 |
| 17500 | 52.58 | 26.74 |
| 19000 | 49.57 | 10.43 |
| 20000 | 53.29 | 2.98 |









A. Performance and quality attributes and conditions not expressly stated in this specification document are intended to be excluded and do not form a part of this specification document.


B. Electrical specifications and performance data contained in this specification document are based on Mini-Circuit's applicable established test performance criteria and measurement instructions.

C. The parts covered by this specification document are subject to Mini-Circuits standard limited warranty and terms and conditions (collectively, "Standard Terms"); Puchasers of this part are entitled to the rights and benefits contained therein. For a full statement of the Standard Terms and the exclusive rights and remedies thereunder, please visit Mini-Circuits' website at www.minicircuits.com/MCLStore/terms.jsp

Coaxial Connections

| INPUT | SMA-Male |
|--------|------------|
| OUTPUT | SMA-Female |

Outline Drawing



Outline Dimensions (inch mm)

| wt. | Е | D | В |
|-------|------|-------|-------|
| grams | .312 | 2.67 | .410 |
| 17.0 | 7.92 | 67.82 | 10.41 |

Note: Please refer to case style drawing for details

Notes
A. Performance and quality attributes and conditions not expressly stated in this specification document are intended to be excluded and do not form a part of this specification document.

B. Electrical specifications and performance data contained in this specification document are based on Mini-Circuit's applicable established test performance criteria and measurement instructions.

C. The parts covered by this specification document are subject to Mini-Circuits standard limited to the rights and benefits contained therein. For a full statement of the Standard Terms and the exclusive rights and remedies thereunder, please visit Mini-Circuits' website at www.minicircuits.com/MCLStore/terms/jsp

