## DC Pass Directional Coupler

## **ZADC-ED12621/1**

## **Important Note**

This model has been designed, built and tested in our engineering department. Performance data represents model capability.

At present it is a non-catalog model. On request, we can supply a final specification sheet, part number and price/delivery information.



Please click "Back", and then click "Contact Us" for Applications support.

**CASE STYLE: CC51-1** 

ELECTRICAL SPECIFICATIONS 50Ω @ +25°C					
Parameter		Min.	Тур.	Max.	Units
Frequency		800		1600	MHz
Coupling	Nominal		20±0.6		dB
	Flatness		± 0.73		dB
Mainline Loss **	800-1600 MHz		0.70		dB
Directivity	800-1600 MHz		20		dB
VSWR	800-1600 MHz		1.20		(:1)
RF Power Input	800-1600 MHz			5	W

Note: \*\* Mainline loss includes theoretical coupled power loss of 0.044dB at 20dB coupling.

MAXIMUM RATINGS			
Operating Temperature	-55°C to 100°C		
Storage Temperature	-55°C to 100°C		
DC Current	2A		

COAXIAL CONNECTIONS				
INPUT	1			
OUTPUT	3			
COUPLED FORWARD	2			

## DC+RFOUTPUT DC+RFOUTPUT INTERNAL SEMENTAL SEME

\* ELECTRICAL SCHEMATIC FOR DIRECTIONAL COUPLER THAT IS DESIGNED WITHOUT INTERNAL TRANSFORMERS.