Coaxial

Diplexer

50O 9.8 to 2000 MHz (9.8-10.2, 650-2000 MHz)

The Big Deal

- Low insertion loss
- High Rejection
- Connectorized package





Generic photo used for illustration purposes only CASE STYLE: FL905

Product Overview

ZX75-23-S+ is a low-pass + high-pass combination device. Low pass port is designed for 9.8 to 10.2 MHz and high pass port is designed for 650 to 2000 MHz. This diplexer is used to pass IF, pilot carrier or clock synchronizing signal. This diplexer can also be used in various systems including satellite, CATV and multiband radio systems.

Key Features

Feature	Advantages		
Low passband insertion loss	Suitable for high performance application.		
Extended stopband rejection	Spurious rejection and avoids using additional filters.		
Connectorized package	The connectorized package is easy to interface with other devices and well suited for test setups.		

A Performance and quality attributes and conditions not expressly stated in this specification document are intended to be excluded and do not form a part of this specification document. B. Electrical specifications and performance data contained in this specification document are based on Mini-Circuit's applicable established test performance criteria and measurement instructions. C. The parts covered by this specification document are subject to Mini-Circuit's standard limited warranty and terms and conditions (collective), "Standard Terms"); Purchasers of this part are entitled to the rights and benefits contained therein. For a full statement of the Standard Terms and the exclusive rights and remedies thereunder, please visit Mini-Circuit's website at www.minicicuits.com/WCLStore/terms.jsp



Notes

Coaxial Diplexer

9.8 to 2000 MHz (9.8-10.2, 650-2000 MHz) 50Ω


Maximum Ratings

Operating Temperature	-40°C to 85°C
Storage Temperature	-55°C to 100°C
RF Power Input	400mW at 25°C
Permanent damage may occur if any o	of these limits are exceeded.

Pin Connections

HIGH PASS PORT	1
LOW PASS PORT	2
COMMON PORT	3

Outline Drawing



Outline Dimensions (inch)

A .74 18.80	B .90 22.86	C .54 13.72	D .50 12.70	E .04 1.02	F .16 4.06	G .29 7.37
H .37 9.40	J 	K .122 3.10	L .496 12.60	M .106 2.69	N .122 3.10	wt grams 20.0
Note:	Please	refer to	case si	tyle drav	ving fo	r details

Notes

Features

- Low insertion loss
- 50Ω Impedance
- · Combination of Low pass and High pass filters
- · Connectorized package

Applications

- · Clock synchronizing signal
- Satellite
- CATV



Generic photo used for illustration purposes only CASE STYLE: FL905

> Connectors Model ZX75-23-S+ SMA

+RoHS Compliant The +Suffix identifies RoHS Compliance. See our web site for RoHS Compliance methodologies and qualifications


Electrical Specifications at 25°C

Parameter		Port	Frequency (MHz)	Min.	Тур.	Max.	Unit
	Insertion Loss	Low Pass	9.8-10.2	-	0.5	1.0	dB
		High Pass	650-2000	-	0.5	1.0	uв
	Return Loss	Low Pass	9.8-10.2	11	18	-	
Pass Band		High Pass	650-2000	11	18	-	dB
		0	9.8-10.2	11	18	-	
		Common	650-2000	11	18	-	
Sten Band Isolat		Low Pass	50-2700	20	36	-	- D
	lation		Low Pass	650-2000	-	52	-
Stop Band Isolation		High Pass	DC-270	20	31	-	٩Þ
			9.8-10.2	-	90	-	dB

Typical Performance Data at 25°C

FREQUENCY (MHz)		ON LOSS B)	RETURN LOSS (dB)			
	Low Pass Port	High Pass Port	Common Port	Low Pass Port	High Pass Port	
0.5	0.34	93.34	28.34	28.42	0.00	
9.8	0.48	93.68	19.95	19.16	0.00	
10.2	0.49	95.02	20.18	19.38	0.00	
20.0	1.17	98.30	14.16	15.32	0.00	
30.0	11.08	92.74	1.20	1.84	0.00	
40.0	25.01	90.28	0.39	0.78	0.00	
50.0	36.55	86.20	0.25	0.51	0.00	
150.0	55.68	59.20	0.06	0.09	0.03	
270.0	57.07	31.52	0.09	0.05	0.13	
350.0	57.55	18.64	0.22	0.04	0.32	
400.0	58.29	11.80	0.57	0.04	0.71	
450.0	60.23	6.09	1.76	0.04	1.96	
480.0	62.23	3.57	3.40	0.04	3.63	
500.0	63.69	2.37	5.05	0.04	5.31	
650.0	62.66	0.31	24.49	0.04	26.69	
750.0	61.76	0.29	18.54	0.04	19.44	
1000.0	60.49	0.24	18.81	0.06	19.65	
1250.0	59.18	0.20	21.26	0.07	22.03	
1500.0	58.18	0.18	24.37	0.08	25.09	
2000.0	55.65	0.24	29.14	0.11	29.69	
2200.0	53.76	0.46	36.26	0.12	25.03	
2700.0	52.48	0.23	21.59	0.31	21.42	

Functional Schematic



A Performance and quality attributes and conditions not expressly stated in this specification document are intended to be excluded and do not form a part of this specification document. B. Electrical specifications and performance data contained in this specification document are based on Mini-Circuit's applicable established test performance criteria and measurement instructions. C. The parts covered by this specification document are subject to Mini-Circuit's standard limited warranty and terms and conditions (collectively, "Standard Terms"); Purchasers of this part are entitled to the rights and benefits contained therein. For a full statement of the Standard Terms and conditions (collectively).

REV.C ECO-009261 ZX75-23-S+ EDU1383 URJ 210814 Page 2 of 3

Mini-Circuits®

www.minicircuits.com P.O. Box 350166, Brooklyn, NY 11235-0003 (718) 934-4500 sales@minicircuits.com

0


10

20


30 40

50

Insertion Loss (dB)





Frequency (MHz)



ZX75-23-S+ LOW PASS PORT

INSERTION LOSS (Pin=0dBm)





Notes A Performance and quality attributes and conditions not expressly stated in this specification document are intended to be excluded and do not form a part of this specification document. B. Electrical specifications and performance data contained in this specification document are based on Mini-Circuit's applicable established test performance criteria and measurement instructions. C. The parts covered by this specification document are subject to Mini-Circuit's standard limited warranty and terms and conditions (collectively, "Standard Terms"); Purchasers of this part are entitled to the rights and benefits contained therein. For a full statement of the Standard Terms and the exclusive rights and remedies thereunder, please visit Mini-Circuit's vebsite at www.minicircuits.com/MCLStore/terms.jsp

⊒Mini-Circuits