

## Typical Performance Data

FREQUENCY (MHz)	AVERAGE INSERTION LOSS (dB)	INPUT RETURN LOSS (dB)	AMPLITUDE UNBALANCE (dB)	PHASE UNBALANCE (deg)
1	0.51	24.06	0.07	0.01
4	0.35	26.91	0.07	0.01
10	0.34	27.13	0.07	0.01
60	0.41	25.93	0.08	0.02
100	0.44	24.45	0.11	0.04
140	0.52	23.03	0.14	0.15
200	0.53	21.02	0.21	0.50
300	0.62	18.02	0.38	0.70
400	0.70	15.36	0.64	1.76
500	0.70	12.96	0.98	3.67