

# Fixed Attenuator

# BW-KM3-2W44+

## Typical Performance Data

FREQUENCY (MHz)	ATTENUATION (dB)	VSWR (:1)
100	2.68	1.02
1000	2.71	1.02
2000	2.73	1.03
3000	2.73	1.03
4000	2.74	1.04
5000	2.75	1.04
6000	2.77	1.04
7000	2.78	1.06
8000	2.79	1.06
9000	2.80	1.06
10000	2.82	1.07
11000	2.83	1.07
12000	2.84	1.07
13000	2.86	1.07
14000	2.87	1.06
15000	2.89	1.07
16000	2.90	1.07
17000	2.92	1.07
18000	2.94	1.08
19000	2.96	1.09
20000	2.98	1.10
21000	2.99	1.11
22000	2.99	1.11
23000	3.02	1.12
24000	3.08	1.12
25000	3.11	1.12
26000	3.13	1.13
27000	3.14	1.13
28000	3.17	1.13
29000	3.19	1.14
30000	3.22	1.15
31000	3.25	1.17
32000	3.29	1.18
33000	3.31	1.19
34000	3.35	1.20
35000	3.37	1.19
36000	3.40	1.17
37000	3.42	1.15
38000	3.45	1.14
39000	3.48	1.12
40000	3.51	1.08