

Fixed Attenuator

BW-KM6-2W44+

Typical Performance Data

FREQUENCY (MHz)	ATTENUATION (dB)	VSWR (:1)
100	5.66	1.01
1000	5.68	1.01
2000	5.70	1.01
3000	5.71	1.02
4000	5.73	1.02
5000	5.73	1.03
6000	5.75	1.03
7000	5.76	1.04
8000	5.77	1.04
9000	5.78	1.04
10000	5.80	1.04
11000	5.81	1.04
12000	5.83	1.04
13000	5.85	1.04
14000	5.87	1.05
15000	5.89	1.05
16000	5.91	1.06
17000	5.93	1.06
18000	5.94	1.07
19000	5.97	1.07
20000	5.99	1.08
21000	6.01	1.08
22000	6.03	1.07
23000	6.05	1.07
24000	6.08	1.07
25000	6.10	1.07
26000	6.13	1.07
27000	6.15	1.07
28000	6.18	1.08
29000	6.21	1.09
30000	6.25	1.10
31000	6.27	1.11
32000	6.31	1.12
33000	6.34	1.13
34000	6.38	1.14
35000	6.41	1.14
36000	6.45	1.13
37000	6.47	1.12
38000	6.50	1.10
39000	6.51	1.08
40000	6.52	1.06