

# Coaxial SMA Band Pass Filter

# VBFZ-1400-S+

## Typical Performance Data

FREQUENCY (MHz)	INSERTION LOSS (dB)	RETURN LOSS (dB)
10	86.42	0.00
250	68.43	0.02
870	31.80	0.44
890	29.20	0.49
990	17.27	0.98
1065	9.43	2.35
1132	4.55	6.28
1350	2.05	13.47
1400	1.97	15.88
1450	1.97	18.36
1690	3.82	25.80
1755	8.63	5.84
1812	16.96	2.82
1900	30.79	2.40
1940	37.12	2.44
1965	41.68	2.44
3000	58.86	1.15
5000	50.16	0.38
6600	53.10	0.65
10000	38.71	0.92

REV. OR  
VBFZ-1400-S+  
200810  
Page 1 of 1



IF/RF MICROWAVE COMPONENTS • ISO 9001 ISO 14001 AS 9100 CERTIFIED RoHS compliant  
P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 Fax (718) 332-4661



The Design Engineers Search Engine finds the model you need, Instantly • For detailed performance specs & shopping online see

