

Coaxial SMA Band Pass Filter

VBFZ-2130-S+

Typical Performance Data

FREQUENCY (MHz)	INSERTION LOSS (dB)	RETURN LOSS (dB)
50	79.71	0.00
500	80.20	0.04
1010	59.20	0.16
1400	35.53	0.44
1420	33.32	0.47
1605	14.83	1.29
1684	7.90	3.09
1753	3.93	7.61
2000	1.92	11.40
2130	1.88	11.57
2260	1.76	17.21
2540	3.39	11.24
2635	6.41	11.25
2710	13.61	4.64
2795	25.49	2.40
2840	32.11	2.02
2950	39.28	1.87
7000	45.16	0.46
10000	44.11	3.38
18000	34.85	12.82

REV. OR
VBFZ-2130-S+
200810
Page 1 of 1



IF/RF MICROWAVE COMPONENTS • ISO 9001 ISO 14001 AS 9100 CERTIFIED RoHS compliant
P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 Fax (718) 332-4661



The Design Engineers Search Engine finds the model you need, Instantly • For detailed performance specs & shopping online see

