

# Coaxial SMA Band Pass Filter

# VBFZ-2575-S+

## Typical Performance Data

FREQUENCY (MHz)	INSERTION LOSS (dB)	RETURN LOSS (dB)
50	80.64	0.03
500	77.72	0.08
1275	33.69	0.22
1390	27.36	0.27
1477	22.52	0.40
1590	16.11	0.64
1720	8.53	1.64
1801	4.71	3.74
1865	2.90	6.47
2350	1.68	10.27
2575	1.77	9.39
2800	1.57	13.69
3119	3.68	6.19
3262	7.36	2.98
3405	11.94	2.17
3682	23.22	1.76
3850	32.35	1.37
3900	35.36	1.22
7000	35.60	0.49
9000	27.72	0.37

REV. OR  
VBFZ-2575-S+  
200811  
Page 1 of 1



IF/RF MICROWAVE COMPONENTS • ISO 9001 ISO 14001 AS 9100 CERTIFIED RoHS compliant  
P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 Fax (718) 332-4661



The Design Engineers Search Engine finds the model you need, Instantly • For detailed performance specs & shopping online see

