

# Coaxial SMA Band Pass Filter

# VBFZ-5500-S+

## Typical Performance Data

FREQUENCY (MHz)	INSERTION LOSS (dB)	RETURN LOSS (dB)
50	60.32	0.02
1500	37.93	0.11
3500	35.51	0.35
3600	41.94	0.44
3750	30.57	0.57
4000	15.08	1.02
4150	8.84	2.10
4300	4.47	4.87
4450	2.28	10.11
4900	1.14	29.18
5500	1.26	15.06
6200	1.27	17.11
6800	2.83	7.73
7000	4.82	4.40
7300	8.94	2.48
7700	15.82	1.98
8200	28.73	1.48
8600	48.53	1.16
10000	39.46	1.66
17000	34.71	13.61

REV. OR  
VBFZ-5500-S+  
200811  
Page 1 of 1



IF/RF MICROWAVE COMPONENTS • ISO 9001 ISO 14001 AS 9100 CERTIFIED RoHS compliant  
P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 Fax (718) 332-4661



The Design Engineers Search Engine finds the model you need, Instantly • For detailed performance specs & shopping online see

