

# Coaxial SMA Band Pass Filter

# VBFZ-925-S+

## Typical Performance Data

FREQUENCY (MHz)	INSERTION LOSS (dB)	RETURN LOSS (dB)
10	82.20	0.00
80	64.21	0.01
250	57.35	0.07
500	31.16	0.46
530	25.79	0.59
595	15.40	1.16
643	8.76	2.49
670	5.89	4.12
702	3.60	7.42
800	1.68	20.11
925	1.64	13.87
1050	2.16	9.87
1275	5.42	7.70
1350	11.88	3.80
1435	21.92	1.89
1550	28.36	1.13
1620	30.79	0.99
3000	54.45	0.30
8000	54.31	2.08
18000	34.91	11.88

REV. OR  
VBFZ-925-S+  
200808  
Page 1 of 1



IF/RF MICROWAVE COMPONENTS • ISO 9001 ISO 14001 AS 9100 CERTIFIED RoHS compliant  
P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 Fax (718) 332-4661



The Design Engineers Search Engine finds the model you need, Instantly • For detailed performance specs & shopping online see

